




LED EMERGENCY EXIT BOX SIGNS + SELF-TEST OPTION

Low energy alternative to standard emergency exit signs - perfect for office, commercial and industrial applications

- Steel construction • LED charge light • Facility for remote switching
- 3 hour maintained mode as standard which can also be configured for non maintained operation
- Diffuser on base: for added downward illumination of escape route
- Long life energy efficient LED light source eliminates lamp replacement cycle without compromising panel visibility distance
- Battery test button
- Battery - Ni-Cd 3.6V 1500Ah
- Battery 1 year warranty - Replacement battery code: EB4

SEEXIT3ML: Automatic testing in accordance with BS EN 62034



Hole knockouts on each side of fitting

Code	Version / Legend Set Included	Wattage	Lumens	Avg. Rated Life (Hrs)	IP Rating	Viewing Distance	MOM / OPQ
EXIT3MLED	Signs Directive Down Arrow	4W	55 lm	30,000 hrs	IP20	32m	6 / 6
SEEXIT3ML	Self Test / ISO 7010 Up Arrow						

Accessories			
Signs Directive	ISO 7010	Version	MOM / OPQ
EBLGD	ISOEBLGD	Left Arrow Legend	1 / 100
EBLGDR	ISOEBLGDR	Right Arrow Legend	
EBLGDU	ISOEBLGDU	Up Arrow Legend	
	ISOEBLGDD	Down Arrow Legend	



5 Year Warranty

